

RGB MATRIX PREAMPLIFIER

The TDA2532 is an integrated matrix preamplifier for use in conjunction with discrete video amplifiers to provide RGB drive to the cathodes of a colour television picture tube. The integrated circuit incorporates:

- matrix circuits;
- gain control stages, operated by d.c. setting;
- preamplifiers with feedback and integral black-level clamps;
- facilities for video blanking during data display.

The three channels have the same layout to ensure identical frequency behaviour. The integrated circuit has been designed to be driven by the integrated colour demodulator combination type TDA2522.

QUICK REFERENCE DATA

Supply voltage	V ₉₋₁₆	typ.	12 V
Operating ambient temperature range	T _{amb}	—25 to +60 °C	
Luminance input resistance	R ₁₋₁₆	>	100 kΩ
Input current of colour difference inputs	I _{2, I₄, I₆}	typ.	1 μA
Clamping pulse input current	—I ₈	<	60 μA
Gain of RGB preamplifiers	G	typ.	0 dB
Gain d.c. adjustment range	ΔG	>	± 40 %
Gain of error amplifier (transconductance)		typ.	20 mA/V
Output current swing	I _{10, I₁₂, I₁₄}	typ.	± 3,5 mA


PACKAGE OUTLINES

TDA2532: 16-lead DIL; plastic (SOT-38).
TDA2532Q: 16-lead QIL; plastic (SOT-58).

201

June 1978

BLOCK DIAGRAM



June 1978

702

RATINGS

Limiting values in accordance with the Absolute Maximum System (IEC 134)

Supply voltage (pin 9)	V_p (V9-16)	max.	13,2 V
Pin 1	$V_{1\cdot16}$		0 to V_p
Pins 3, 5	$V_{3\cdot5\cdot16}$		0 to V_p
Pins 2, 4 and 6	$V_{2\cdot4\cdot6\cdot16}$		0 to V_p
Pin 7	$V_{7\cdot16}$		-0,5 V to V_p
Pin 8	$V_{8\cdot16}$	max.	V_p
Pin 10	$V_{10\cdot16}$		$V_{11\cdot16}$ to $V_p + 3$ V
Pin 12	$V_{12\cdot16}$		$V_{13\cdot16}$ to $V_p + 3$ V
Pin 14	$V_{14\cdot16}$		$V_{15\cdot16}$ to $V_p + 3$ V
Pins 11, 13 and 15	$V_{11\cdot13\cdot15\cdot16}$		0,3 V_p to V_p
Pin 8	-18	max.	1 mA
Total power dissipation	P_{tot}	max.	1,1 W
Storage temperature	T_{stg}		-25 to +125 °C
Operating ambient temperature	T_{amb}		-25 to +60 °C

CHARACTERISTICSAt $V_p = 12$ V; $V_{1\cdot16} = 1,5$ V; $T_{amb} = 25$ °C; measured in circuit on page 6.

Current consumption	I_g	typ.	60 mA
---------------------	-------	------	-------

Luminance input

Black level	$V_{1\cdot16}$	typ.	1,5 V
Black-to-white input voltage (peak-to-peak value)	$V_{1\cdot16}$ (p-p)	typ.	1,0 V
Input resistance	$R_{1\cdot16}$	>	100 kΩ

Colour difference input

Input signals (peak-to-peak values) for 100% saturated colour bars	R-Y	$V_{6\cdot16}$ (p-p)	typ.	1,4 V
	G-Y	$V_{4\cdot16}$ (p-p)	typ.	0,82 V
	B-Y	$V_{2\cdot16}$ (p-p)	typ.	1,78 V
Input currents (source resistance 300 Ω max.)	I_2, I_4, I_6	typ.	<	1 μA 3 μA

203

June 1978

CHARACTERISTICS (continued)

Clamp pulse input

Input voltage for clamping

on level	V ₈₋₁₆	7,5 to 12 V
off level	V ₈₋₁₆	0 to 6,5 V*

Input voltage to enable video blanking input

V ₈₋₁₆	<	1 V
-------------------	---	-----

Input voltage to disable video blanking input

V ₈₋₁₆	>	2 to 12 V
-------------------	---	-----------

Input current for clamping

on level	I ₈	<	1 μA
off level	-I ₈	<	60 μA

Clamp pulse duration

t _{clamp}	>	3,5 μs
--------------------	---	--------

Video blanking input

Input voltage for blanking

on level	V ₇₋₁₆	>	1,5 V
off level	V ₇₋₁₆	<	0,5 V

Feedback input

D.C. level during clamping

V _{11; 13; 15-16}	6 to 6,2 V
----------------------------	------------

Gain adjustment for colour drive

Adjustment voltage range

V _{3;5-16}	0 to 10 V
---------------------	-----------

Adjustment voltage for nominal gain

V _{3;5-16}	typ.	5 V
---------------------	------	-----

Nominal gain between colour difference

inputs, luminance input and colour feedback inputs (pins 11, 13 and 15)	G	typ.	0 dB**
--	---	------	--------

Adjustment range of nominal gain

at ΔV _{3;5-16} = ± 5 V	ΔG	>	± 40 %
---------------------------------	----	---	--------

Differential amplifier

Gain of error amplifier (transconductance)

	typ.	20 mA/V
--	------	---------

Output current swing

I _{10, 12, 14}	≥	± 3,5 mA
-------------------------	---	----------

Integrated load resistance

R _{10; 12; 14-9}	typ.	640 Ω▲
---------------------------	------	--------

Output bias voltage (see application
information)

V _{10; 12; 14-16}	typ.	8 V ▲
----------------------------	------	-------

* Switching from clamping on to off occurs at about 7 V.

** Error signal is assumed to be negligible.

▲ The fact that the load resistors have series diodes (D; see block diagram on page 2), means that the resistors can be ignored when V_{10; 12; 14} ≥ V_p. In that case, external load resistors must be chosen such that the nominal current will be 3,5 mA.

APPLICATION INFORMATION (see circuit on page 6)

Clamping level (V_{cl}) of video output stages, with set clamping level potentiometers in their mid-positions:


$$V_{cl} = 0,5 V_P \left(1 + \frac{R_1}{R_2} - \frac{R_1}{R_3}\right).$$

$$\text{Gain of video output stages: } G = 1 + \frac{R_1}{R_2} + \frac{R_1}{R_3} + \frac{R_1}{R_4 + 0,25 R_5}.$$

205

June 1978

APPLICATION INFORMATION



R5 = clamping level adjustment (70 V to 170 V); R6 = gain adjustment (65 to 140).