

2 SC 3842	Si-N	S-L, TV-HA, 600/400V, 10A, 70W, 32MHz	18c	-		
2 SC 3843	Si-N	S-L, TV-HA, 600/450V, 10A, 75W/28MHz	18c	-		
2 SC 3844	Si-N	S-L, TV-HA, 600/450V, 15A, 75W/30MHz	18c	BUW 13 A		18j
2 SC 3845	Si-N	S-L, TV-HA, 1200/800V, 3A, 75W/15MHz	18c	BU 2508 AF		16c
2 SC 3846	Si-N	S-L, TV-HA, 1200/800V, 6A, 80W, 15MHz	18c	2SD1577		16c
2 SC 3847	Si-N	S-L, TV-HA, 1200/800V, 10A, 85W/15MHz	18c	(BUV 70)		18j
2 SC 3850	Si-N	S-L, 500/400V, 20A, 125W, <1/3.5µs	18j	-		
2 SC 3851	Si-N	NF/S-L, lo-sat, 80V, 4A, 25W, 15MHz	17c	2SD1411		17c
2 SC 3851 A	Si-N	=2SC3851: 100V	17c	2SD1411		17c
2 SC 3852	Si-N	hi-beta,lo-sat,80V,3A,25W,15MHz,B>500	17c	(2SD1273)		17c
2 SC 3852 A	Si-N	=2SC3852: 100V	17c	-		
2 SC 3853	Si-N	NF/S-L, 120/80V, 6A, 60W, 20MHz	18j	BD 245 C		18j
2 SC 3854	Si-N	NF/S-L, 160/120V, 8A, 80W, 20MHz	18j	-		
2 SC 3855	Si-N	NF/S-L, 200/140V, 10A, 100W, 20MHz	18j	2SC3263		18j
2 SC 3856	Si-N	NF/S-L, 200/180V, 15A, 130W, 20MHz	18j	2SC3263		18j
2 SC 3857	Si-N	NF/S-L, 200/200V, 15A, 150W, 20MHz	20j	2SC3264		20j
2 SC 3858	Si-N	NF/S-L, 200/200V, 17A, 200W, 20MHz	20j	2SC3264		20j
2 SC 3860	Si-N+R	S, 50V, 0,1A, 0,3W, 250MHz, Rb=10kΩ	40c	(BC 546)		18
2 SC 3861	Si-N	UHF, 10V, 0,01A, 0,07W, 4GHz	7f	2SC2570 A		7f
2 SC 3863	Si-N+R	=2SC3864: SMD	35a	-		
2 SC 3864	Si-N+R	S,Rb=2,2k,Rbe=10k,50V,0,1A,0,3W,250MHz	40c	(BC 546)		7a
2 SC 3865	Si-N	S-Reg, 500/400V, 5A, 40W, <500/1650ns	17c	2SC3752		17c
2 SC 3866	Si-N	S-L, 900/800V, 3A, 40W, <1000/4800ns	17c	BUT 11 AF		17c
2 SC 3868	Si-N	S-L, 500/400V, 1,5A, 25W, <700/2300ns	17c	-		
2 SC 3869	Si-N	S-L, 500/400V, 5A, 35W, <700/2300ns	17c	-		
2 SC 3870	Si-N	S-L, 500/400V, 7A, 40W, <700/2300ns	17c	-		
2 SC 3871	Si-N	S-L, 500/400V, 10A, 45W, <700/2300ns	17c	-		
2 SC 3872	Si-N	S-L, 500/400V, 10A, 70W, <700/2300ns	16c	-		
2 SC 3873	Si-N	S-L, 500/400V, 12A, 100W, <700/2300ns	16c	-		
2 SC 3874	Si-N	S-L, 500/400V, 15A, 150W, <700/2300ns	77j	-		
2 SC 3875	Si-N	SMD, Uni, ra, 60V, 0,15A, 130MHz	35b	-		
2 SC 3876	Si-N	SMD, Uni, 35V, 0,5A, 300MHz	35b	-		
2 SC 3878	Si-N	SMD, Uni, ra, 35V, 0,1A, 120MHz	35b	-		
2 SC 3879	Si-N	SMD, FM-ZF, 35V, 0,05A, 175MHz	35b	-		
2 SC 3880	Si-N	SMD, FM/VHF, 40V, 0,02A, 550MHz	35b	-		
2 SC 3881	Si-N	SMD, FM/VHF, 30V, 0,05A, 600MHz	35b	-		
2 SC 3883	Si-N+Di	TV-HA, 1500/800V, 5A, 50W	18j	BU 2508 D,DW		18j, 16j
2 SC 3884	Si-N	SN, HA, hi-res, 1400/600V, 6A, 50W	18c	2SC3886 A		18c
2 SC 3884 A	Si-N	=2SC3884: 1500/600V	18c	2SC3886 A		18c
2 SC 3885	Si-N	SN, HA, hi-res, 1400/600V, 7A, 50W	18c	2SC3886 A		18c
2 SC 3885 A	Si-N	=2SC3885: 1500/600V	18c	2SC3886 A		18c
2 SC 3886	Si-N	SN, HA, hi-res, 1400/600V, 8A, 50W	18c	2SC3886 A		18c
2 SC 3886 A	Si-N	=2SC3886: 1500/600V	18c	2SC3886 A		18c
2 SC 3887(A)	Si-N	=2SC3884(A): 80W	77c,j	2SC4560		77j
2 SC 3888(A)	Si-N	=2SC3885(A): 80W	77c,j	2SC4560		77j
2 SC 3889(A)	Si-N	=2SC3886(A): 80W	77c,j	2SC4560		77j
2 SC 3890	Si-N	S-Reg, 500/400V, 7A, 30W, <1000/3500ns	17c	BUT 12 AF		17c
2 SC 3891	Si-N+Di	=2SC3884: int. Damper-Diode	18c	(BU 2508 DF)		16c
2 SC 3892	Si-N+Di	=2SC3885: int. Damper-Diode	18c	(BU 2508 DF)		16c
2 SC 3892 A	Si-N+Di	=2SC3885A: int. Damper-Diode	18c	(BU 2508 DF)		16c
2 SC 3893	Si-N+Di	=2SC3886: int. Damper-Diode	18c	(BU 2508 DF)		16c
2 SC 3893 A	Si-N+Di	=2SC3886A: int. Damper-Diode	18c	(BU 2508 DF)		16c
2 SC 3894	Si-N	HA, hi-def, 1500/800V, 6A, 60W	18c	BU 2508 AF		16c
2 SC 3895	Si-N	HA, hi-def, 1500/800V, 7A, 60W	18c	BU 2508 AF		16c
2 SC 3896	Si-N	HA, hi-def, 1500/800V, 8A, 70W	18c	2SC3886 A		18c
2 SC 3897	Si-N	HA, hi-def, 1500/800V, 10A, 70W	18c	2SC4924		18c